













# LSBREM XTREME DUTY • 7YR













## HANDHELD REMOTE FOR SPECTRA™ BACK-LIT PANEL

### OPERATING INSTRUCTIONS



Batteries not included.  
Requires 2 - AAA.

 	<p> Turn ON       Turn OFF</p> <p>Hand held remote controller cannot be used directly as the only on-off switch it should be used together with the switch. The fixture needs to be turned off for the night with a standard hard-wired wall switch (or at the breaker panel).</p>
	Turn off the light to save the current color temperature then turn on the light, the last saved color temperature will be displayed by default.
	<p><b>MATCHING CODE FOR LIGHT</b></p> <p>Holding the 'ID' button will keep the controller's indicator on, then turn on the light and release the 'ID' button, matching code complete. Matching code for several lights simultaneously is available.</p>
	<p><b>RELEASE THE CODE AND DISCONNECT LIGHT FROM REMOTE CONTROLLER</b></p> <p>Press the bottom  +  together, then turn on the light, to finish releasing the code on the lights.</p>
	<p><b>GROUP SELECTING BUTTON</b></p> <p>Grouping lights (matching code process needs to be completed first). Turn off the lights, continue pressing the group selection button for 3s, then turn on the lights the lights will flash to finish grouping.</p>
	<p><b>SAVE BUTTON</b></p> <p>Press and hold (3-5 seconds) the "SAVE" button until the light goes out, the current brightness and color temperature are automatically saved. Turn off lights then turn on, the last saved brightness and color temperature will be displayed by default.</p>
	<b>ALL GROUPS ARE SELECTED</b>

COLOR TEMPERATURE AND BRIGHTNESS SELECTION			
			
Color Temperature			
			
Brightness			
			
Increase Brightness	Decrease Brightness	Decrease Color Temperature	Increase Color Temperature

Power the light off then power it on, the last saved brightness (which is saved by the button "SAVE") and the last saved color temperature (which is saved by the button "SAVE" or "OFF") will be displayed by default. The defaulted factory setting of the light is 100% brightness and 4000K.